### DATASHEET - DS7-34DSX032N0-D



Soft starter, 32 A, 200 - 480 V AC, 24 V DC, Frame size: FS2, Communication Interfaces: SmartWire-DT



Part no.DS7-34DSX032N0-DCatalog No.134950Alternate CatalogDS7-34DSX032N0-DNo.EL-Nummer(Norway)0004137338

## **Delivery program**

Product range			SmartWire-DT slave
Subrange			SmartWire-DT Soft starters
Description			With internal bypass contacts
Function			Soft starters for three-phase loads
Mains supply voltage (50/60 Hz)	U <sub>LN</sub>	V AC	200 - 480
Supply voltage	Us		24 V DC
Control voltage	U <sub>C</sub>		24 V DC
Assigned motor rating (Standard connection, In-Line)			
at 400 V, 50 Hz	Р	kW	15
at 460 V, 60 Hz	Ρ	HP	25
Rated operational current			
AC-53	le	А	32
Rated operational voltage	U <sub>e</sub>		200 V 230 V 400 V 480 V
Connection to SmartWire-DT			yes
Frame size			FS2

# Technical data

General			
Standards			IEC/EN 60947-4-2 UL 508 CSA22.2-14
Approvals			CE
Approvals			UL CSA C-Tick UkrSEPRO
Climatic proofing			Damp heat, constant, to IEC 60068-2-3 Damp heat, cyclic, to IEC 60068-2-10
Ambient temperature			
Operation	θ	°C	-5 - +40 up to 60 at 2% derating per Kelvin temperature rise
Storage	9	°C	-25 - +60
Altitude		m	0 - 1000 m, above that 1 % derating per 100 m , up to 2000 m
Mounting position			Vertical
Degree of protection			
Degree of Protection			IP20
Protection against direct contact			Finger- and back-of-hand proof
Overvoltage category/pollution degree			II/2
Shock resistance			8 g/11 ms
Vibration resistance to EN 60721-3-2			2M2
Radio interference level (IEC/EN 55011)			В
Static heat dissipation, non-current-dependent	P <sub>vs</sub>	W	1.5
Weight		kg	0.46

Main conducting paths			
Rated operating voltage	Ue	V AC	200 - 480
Supply frequency	f <sub>LN</sub>	Hz	50/60
Rated operational current	le	A	
AC-53	l <sub>e</sub>	A	32
Assigned motor rating (Standard connection, In-Line)	.6		-
at 230 V, 50 Hz	Р	kW	7.5
at 200 V, 50 Hz	P	kW	15
at 200 V, 60 Hz	P	HP	10
at 200 V, 60 Hz at 230 V, 60 Hz	P	HP	10
at 200 V, 60 Hz at 460 V, 60 Hz	P	HP	25
Overload cycle to IEC/EN 60947-4-2	r	III	23
AC-53a			32 A: AC-53a: 3 - 5: 75 - 10
Internal bypass contacts			√
Short-circuit rating			
Type "1" coordination			PKM0-32 (+ CL-PKZ0)
Type "2" coordination (additional with the fuses for coordination type "1")			3 x 170M1366
Fuse base (number x part no.)			3 x 170H1007
Terminal capacities			3 x 1/01100/
Cable lengths			
Solid		mm <sup>2</sup>	1 x (0.75 - 16) 2 x (0.75 - 10)
Flexible with ferrule		mm <sup>2</sup>	1 x (0.75 - 16) 2 x (0.75 - 10)
Stranded		mm <sup>2</sup>	1 x 16
Solid or stranded		AWG	18 - 6
Tightening torque		Nm	3.2
Screwdriver (PZ: Pozidriv)		mm	PZ2; 1 x 6 mm
Control cables			
Solid		mm <sup>2</sup>	1 x (0.5 - 2.5) 2 x (0.5 - 1.0)
Flexible with ferrule		mm <sup>2</sup>	1 x (0.5 - 1.5) 2 x (0.5 - 0.75)
Solid or stranded		AWG	18 - 14
Tightening torque		Nm	1.2
Screwdriver		mm	0,6 x 5,5 1 x 6
Control circuit			
Digital inputs			
Control voltage			
DC-operated		V DC	24 V DC +10 %/- 15 % oder über SWD
Current consumption 24 V		mA	
External 24 V		mA	1.6
Pick-up voltage		x U <sub>s</sub>	
DC-operated		V DC	17.3 - 27
Drop-out voltage	x U <sub>s</sub>		
DC operated		V DC	0 - 3
Pick-up time			
DC operated		ms	250
Drop-out time			
DC operated		ms	350
Regulator supply			
Voltage	Us	V	24 V DC +10 %/- 15 %
Current consumption	le	mA	50
Notes			External supply voltage

Relay outputs

09/03/2020

Number		2 (TOR, Ready)
Voltage range	V AC	250
AC-11 current range	A	1 A, AC-11
Soft start function		
Ramp times		
Acceleration	S	1 - 30
Deceleration	s	0 - 30
Start voltage (= turn-off voltage)	%	30 100
Start pedestal	%	30 - 100
Current limitation		(0 - 8) × I <sub>e</sub>
Fields of application		
Fields of application		Soft starting of three-phase asynchronous motors
1-phase motors		•
3-phase motors		$\checkmark$
Functions		
Fast switching (semiconductor contactor)		- (minimum ramp time 1s)
Soft start function		✓
Reversing starter		External solution required
Suppression of closing transients		$\checkmark$
Current limitation		●, with PKE
Fault memory	Faults	8
Suppression of DC components for motors		$\checkmark$
Potential isolation between power and control sections		$\checkmark$
Communication Interfaces		SmartWire-DT
Notes		

Rated impulse withstand voltage:

1.2 μs/50 μs (rise time/fall time of the pulse to IEC/EN 60947-2 or -3)
Applies for control circuit/power section/enclosure

# Design verification as per IEC/EN 61439

In	А	32
P <sub>vid</sub>	W	0
P <sub>vid</sub>	W	1.5
P <sub>vs</sub>	W	1.5
P <sub>diss</sub>	W	0
	°C	-5
	°C	40
		Meets the product standard's requirements.
		Meets the product standard's requirements.
		Meets the product standard's requirements.
		Meets the product standard's requirements.
		Meets the product standard's requirements.
		Does not apply, since the entire switchgear needs to be evaluated.
		Does not apply, since the entire switchgear needs to be evaluated.
		Meets the product standard's requirements.
		Does not apply, since the entire switchgear needs to be evaluated.
		Meets the product standard's requirements.
		Does not apply, since the entire switchgear needs to be evaluated.
		Does not apply, since the entire switchgear needs to be evaluated.
		Is the panel builder's responsibility.
		Is the panel builder's responsibility.
	P <sub>vid</sub> P <sub>vid</sub> P <sub>vs</sub>	P <sub>vid</sub> W P <sub>vid</sub> W P <sub>vs</sub> W P <sub>diss</sub> W °C

10.9 Insulation properties	
10.9.2 Power-frequency electric strength	Is the panel builder's responsibility.
10.9.3 Impulse withstand voltage	Is the panel builder's responsibility.
10.9.4 Testing of enclosures made of insulating material	Is the panel builder's responsibility.
10.10 Temperature rise	The panel builder is responsible for the temperature rise calculation. Eaton will provide heat dissipation data for the devices.
10.11 Short-circuit rating	Is the panel builder's responsibility. The specifications for the switchgear must be observed.
10.12 Electromagnetic compatibility	Is the panel builder's responsibility. The specifications for the switchgear must be observed.
10.13 Mechanical function	The device meets the requirements, provided the information in the instruction leaflet (IL) is observed.

### **Technical data ETIM 7.0**

Low-voltage industrial components (EG000017) / Soft starter (EC000640)

Electric engineering, automation, process control engineering / Low-voltage switch technology / Load breakout, motor breakout / Semiconductor motor controller or soft starter (ecl@ss10.0.1-27-37-09-07 [AC0300011])

Rated operation current le at 40 °C Tu	А	32
Rated operating voltage Ue	V	230 - 460
Rated power three-phase motor, inline, at 230 V	kW	7.5
Rated power three-phase motor, inline, at 400 V	kW	15
Rated power three-phase motor, inside delta, at 230 V	kW	0
Rated power three-phase motor, inside delta, at 400 V	kW	0
Function		Single direction
Internal bypass		Yes
With display		No
Torque control		No
Rated surrounding temperature without derating	°C	40
Rated control supply voltage Us at AC 50HZ	V	0 - 0
Rated control supply voltage Us at AC 60HZ	V	0 - 0
Rated control supply voltage Us at DC	V	24 - 24
Voltage type for actuating		DC
Integrated motor overload protection		No
Release class		Other
Degree of protection (IP)		IP20
Degree of protection (NEMA)		1

## Approvals

America     Marking       Specially designed for North America     No       Suitable for     Branch circuits       Current Limiting Circuit-Breaker     No       Max. Voltage Rating     Colored		
Suitable for     Branch circuits       Current Limiting Circuit-Breaker     No       Max. Voltage Rating     80 V	Product Standards	IEC/EN 60947-4-2; GB 14048.6; UL 508; CSA-C22.2 No 0-M91; CSA-C22.2 No 14-05 CE marking
Current Limiting Circuit-Breaker     No       Max. Voltage Rating     480 V	Specially designed for North America	No
Max. Voltage Rating 480 V	Suitable for	Branch circuits
	Current Limiting Circuit-Breaker	No
Degree of Protection IP20; UL/CSA Type 1	Max. Voltage Rating	480 V
	Degree of Protection	IP20; UL/CSA Type 1



