

FREELIGHT 3000

ART. NO. 38450



Freelight is a modular headlamp with 1200-3000 lumen for professionals that require long reach spotlight and extremely bright light. Freelight 3000 is the most powerful headlamp in the Freelight series, combined with a rechargeable 72 Wh battery. The power cord is integrated into the headband and the headlamp features Airflow technology for optimal cooling. FreeLight 3000 is water-resistant according to IP55 and comes with a helmet mount.

FEATURES

- 3000 lumen light output
- Weight 144 g excl. battery / 511 g incl. battery
- Max mode: 3000 lm / 2-4 h burn time / 215 m (705 ft) light distance
- Med Mode: 1000 lm 6.5-13 h burn time / 125 m (410 ft) light distance
- Min mode: 80 lm / 70 h burn time / 45m (148 ft) light distance
- Long distance 72 Wh battery with battery indicator
- 3 brightness levels – ranging from 80 to 3000 lumen
- USB-C Charge cable is included
- More lumen in a smaller lamp head
- Headband with integrated electronics
- Free technology, no cords – no hassle
- Silva Intelligent light – a unique combination of a long reach spotlight and a close flood light
- Silva Flow Light - vary the light pattern depending on your activity
- Air flow system for optimal cooling
- Modular system for easy mix and match of lamp heads and batteries
- Dust protected and water resistant - meets the IP55 standard
- Red safety light at the back of the head

INCLUDED



38317
Free extension
cable 130cm



38234
Free
Headlamp
Battery L 72
Wh



38283
Free Lamp
unit 3000



38341
Free extension
cable 40cm

	True Lumen ANSI	Burn Time ANSI	Light distance ANSI
--	-----------------	----------------	---------------------

MAX	3000 lm	4	215 m
-----	---------	---	-------

MED	1000 lm	13	125 m
-----	---------	----	-------

MIN	80 lm	70	45 m
-----	-------	----	------

Lumen, burn time and light distance are measured according to the [ANSI FL1 STANDARD](#).
Burn time is presented as a span with the lowest and highest value in various conditions.
For more information about ANSI and how different factors affect the burn time and light output: