

FREELIGHT 1200

ART. NO. 38448



The FreeLight is a modular headlamp series for professionals, where you can mix and match lamp units of 1200-3000 lumens with different batteries. FreeLight 1200 provides a light output of 1200 lumens and comes with a 24 Wh rechargeable battery. The power cord is integrated into the headband and the headlamp features Airflow technology for optimal cooling. FreeLight 1200 is dust protected and water-resistant according to IP55 and comes with a helmet mount.

/// FEATURES

- 1200 lumen light output
- Weight 114 g excl. battery / 263 g incl. battery
- Max mode: 1200 lm / 1.5-3 h burn time / 150 m (492 ft) light distance
- Med Mode: 500 lm 4-8 h burn time / 100 m (328 ft) light distance
- Min mode: 80 lm / 25 h burn time / 45m (148 ft) light distance
- A lightweight 24.1 Wh battery with battery indication
- 3 brightness levels – ranging from 80 to 1200 lumens
- USB-C Charge cable is included
- More lumen in a smaller lamp head
- Headband with integrated electronics
- Free technology, no cords – more comfort
- Silva intelligent light – a unique combination of a long reach spotlight and a close flood light
- Air flow technology for optimal cooling through speed wind and convection
- Modular technology for easy mix and match of lamp heads and batteries
- Dust protected and water resistant - meets the IP55 standard
- Red safety light at the back of the head

/// INCLUDED



38281
Free Lamp
unit 1200



38280
Free
Headlamp
Battery S
24.1 Wh



38341
Free extension
cable 40cm

	True Lumen ANSI	Burn Time ANSI	Light distance ANSI
--	-----------------	----------------	---------------------

MAX	1200 lm	3	150 m
------------	---------	---	-------

MED	500 lm	8	100 m
------------	--------	---	-------

MIN	80 lm	25	45 m
------------	-------	----	------

Lumen, burn time and light distance are measured according to the [ANSI FL1 STANDARD](#).
Burn time is presented as a span with the lowest and highest value in various conditions.
For more information about ANSI and how different factors affect the burn time and light output,